



### JANE TOP 2

#### First method:

Simultaneously, press buttons 1 and 2. When the red LED starts flashing. Release the buttons. Press then release the button you want to program. The LED flashes rapidly.

Place your JANE remote control and new remote control as shown below. Press the button of your old remote control



When the LED of your JANE remote control becomes red, this means that the code has been stored

If the code transmitted to your JANE remote control is fixed code, the LED will become green, if it is rolling code, the LED will become green

#### Memorization on the receiver:

Simultaneously, press the buttons 1 and 3 of your new JANE remote control. The red LED will start flashing

Press then release the programmed button, the LED will flash

Wait for approx. 20/25 seconds

NOTE: If this procedure does not memorize your JANE remote control, follow the procedure on your receiver programming manual

When JANE 02 is memorized, it can connect other JANE remote controls

Procedure for the following remote controls:



### Second method: (FM VERSION REMOTE CONTROLS)

Simultaneously, press buttons 3 and 4. When the red LED starts flashing. Release the buttons. Press then release the button you want to program. The LED flashes rapidly

Place your JANE remote control and new remote control as shown below. Press the button of your old remote control



When the LED of your JANE remote control becomes red, the code has been stored

If the code transmitted to your JANE remote control is a fixed code, the LED will become green, if it was rolling code, the LED will become green



### Third method:

For transmitters that can be learned only via the procedure of the original model on the receiver

### Ditec remote controls:



### Nice remote controls:



### Prastel remote controls:



### Procedure for creating rolling code:

1. Press button 2 and 3 and release them when the LED starts flashing
2. Press the "N" button to be programmed
3. The LED flashes rapidly then remains fixed

N 1	NICE FLOR	N 9	ERONE 868
N 2	LIFMASTER 433	N 10	JMC ECO 433
N 3	LIFTMASTER 315	N 12	SILVELOX
N 4	PRASTEL	N 13	DOORHAN
N 5	KINGATES	N 14	LIFTMASTER 390
N 6	DITEC	N 15	CARDIN
N 7	TELCOMA FM	N 16	ECOSTAR
N 8	ERONE 433		