



FERPORT Receiver

Press the push button inside your receiver (the necessary number of impulses)

Impulse	LED1	LED2	LED3	LED4	Output
1	ON	OFF	OFF	OFF	MONOSTABLA CH1
2	OFF	ON	OFF	OFF	BISTABLE CH1
3	ON	ON	OFF	OFF	TIMER CH1
4	OFF	OFF	ON	OFF	MONOSTABLE CH2
5	ON	OFF	ON	OFF	BISTABLE CH2
6	OFF	ON	ON	OFF	TIME CH2
7	ON	ON	ON	OFF	MONOSTABLE CH3
8	OFF	OFF	OFF	ON	BISTABLE CH3
9	ON	OFF	OFF	ON	TIMER CH3
10	OFF	ON	OFF	ON	MONOSTABLA CH4
11	ON	ON	OFF	ON	BISTABLE CH4
12	OFF	OFF	ON	ON	TIMER CH4

Press the button on your remote control, which you want to program

The LED of your receiver comes off

Test you remote control